

January 1992

## ENGINEER'S SPECIFICATION

## EPG Series L800F PumpMaster™ Controller Simplex 3Ø Control Panel

Furnish one EPG Companies Inc., UL listed 508A/698A, Series L800F controller to operate pump motor and auxiliary equipment in manual or automatic mode. The control panel enclosure shall be NEMA type \_\_\_\_.

The enclosure shall be equipped with a window in the outer door, an inner door, a stainless steel drip shield, and a tamper resistant latch. The NEMA 4 (standard) enclosure is finished with polyester urethane paint. The NEMA 4X (optional) enclosure can be either stainless steel or non-metallic.

The control system will operate from a \_\_\_\_ Volt, 60 Hertz, three phase power supply. Pump control components will be sized to operate pump motor of specified horsepower.

The control panel shall include the following as standard features:

**Main Disconnect Switch:** The main disconnect switch shall be \_\_\_\_ Amp rated and will prevent opening of control panel while power is on, and includes \_\_\_\_ Volt, \_\_\_\_ Amp dual element fuses.

**"Hand-Off-Auto" Selector Switch:** Allows manual or automatic operation of the pump motor. The selector switch shall be a heavy duty, oil tight, NEMA 4 rated switch mounted on the inner door. The hand position shall be momentary with a spring return.

**Motor Starter:** The motor starter shall be sized to the pump motor horsepower, and shall be equipped with built in, single phasing protection and ambient compensated, quick-trip adjustable thermal overloads.

**Control Transformer:** A transformer with fused primary and secondary shall isolate the control circuit from the power circuit and provide easier and safer field wiring of accessories. It shall lower incoming voltage to 120 Volts.

**Run Light:** Indicates energization of motor circuit. It shall be heavy duty, oil tight, NEMA 4 rated and shall have an LED lamp with 100,000 hour life. The light shall be mounted on the inner door and will be green in color.

**Motor Overload Light:** Indicates motor not running due to overload condition. It shall be heavy duty, oil tight, NEMA 4 rated and shall have an LED lamp with 100,000 hour life. The light shall be mounted on the inner door and will be red in color.

**Alarm Light:** Indicates high level alarm. It shall be heavy duty, oil tight, NEMA 4 rated and shall have an LED lamp with 100,000 hour life. The light shall be mounted on the inner door and will be red in color.

**Intrinsically Safe Dual Level Relays (IS DLRs):** The level sensing circuits shall be protected by intrinsically safe dual level relays.

**Lightning Arrestor:** Shall be grounded, metal-to-metal, to water strata.

**Terminal Strip:** Labeled and numbered terminal strip provides easy connection of external components.

**Corrosion Inhibitor Emitter:** Inclusion of an industrial corrosion inhibitor emitter shall protect internal components of control panel from corrosion for up to one year and shall be replaceable.

**Options are available to meet specific needs.**

continued on back

## SYSTEM LOGIC AND FUNCTION

The controller is designed to start and stop a pump and annunciate a high level alarm using three float level sensors. The pump starts when the start float is displaced and continues to run until the liquid level decreases to the stop float sensor. If the liquid level rises beyond the pump start float, a high level alarm will be annunciated.